

# Technical Accessory Guides (TAGs)

For Associates, Resellers, ISVs and Alliance Partners

Global



Version: Active-Only

Will only show products that are known to be available for sale

Need to provide an update or change?

Contact <mailto:pgw786@zebra.com>



For Internal Use by  
**PartnerConnect Members Only**



## DS22xx Technical Accessory Guide



NOTE: This document is only for general reference. Solutions Pathway and related PMBs should be used for product availability, pricing, and final solution selection.

\* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.

### Cradles





Part Number	Picture	Description	Notes	Required Items
CR2278-PC10004WW CR2278-PC10004CN (for use in mainland China only)		Presentation Charging/Communication Cradle - Black	<ul style="list-style-type: none"> <li>► Provides radio and charging capabilities</li> <li>► One scanner can be paired per cradle.</li> <li>► Only compatible with DS2278</li> </ul>	Host communication cable and possibly a power supply depending on the host cable type.
CR2278-PC1000BRW		Presentation Charging/Communication Cradle - Healthcare White	<ul style="list-style-type: none"> <li>► Provides radio and charging capabilities</li> <li>► One scanner can be paired per cradle.</li> <li>► Only compatible with DS2278</li> <li>► Used with Healthcare variants of DS2278.</li> <li>► Only available for sale in EMEA, LATAM and APAC.</li> </ul>	Host communication cable and possibly a power supply depending on the host cable type.

### Communication Cables




#### Standard USB Cables

Non-Shielded USB Cable Part Number (recommend using Shielded cable instead for maximum ESD protection)	Shielded USB Cable Part Number	Picture	Description	Notes	Required Items
CBA-U01-S07ZAR	CBA-U21-S07ZBR CBA-U21-S07ZAR - discontinued, now use CBA-U21-S07ZBR - see PMB 3003		USB Cable: Series A Connector, 7ft. Straight	Can also be used with USB Power Supply (PWRWUA5V6W0WW) and Presentation Cradle to create a "charge-only" cradle solution.	
CBA-U10-S15ZAR	CBA-U30-S15ZBR (has heavier gauge wire vs. CBA-U30-S15ZAR, can support 5V and 12V power, scanner dependent) CBA-U30-S15ZAR ► Discontinued 2/2019, now use CBA-U30-S15ZBR - see PMB 10044		USB Cable: Series A Connector, 15ft. Straight		
CBA-U12-C09ZAR	CBA-U32-C09ZAR		USB Cable: (Series A Connector, 9ft. Coiled)		
CBA-U09-C15ZAR	CBA-U29-C15ZBR (has heavier gauge wire vs. CBA-U29-C15ZAR, can support 5V and 12V power, scanner dependent) CBA-U29-C15ZAR ► Discontinued 4/2020, now use CBA-U29-C15ZBR - see PMB 10343		USB Cable: Series A Connector, 15ft. Coiled		



n/a	CBA-U65-S07ZAR		USB Cable: USB-C Connector, 7ft. Straight	► Cable is typically used with tablets and laptops with USB-C ports	
<b>IBM POS USB Cables</b>					
<b>Non-Shielded USB Cable Part Number (recommend using Shielded cable instead for maximum ESD protection)</b>	<b>Shielded USB Cable Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
CBA-U03-S07ZAR	CBA-U23-S07ZBR (has heavier gauge wire vs. CBA-U23-S07ZAR, can support 5V and 12V power, scanner dependent)  CBA-U23-S07ZAR ► Discontinued 2/2019, now use CBA-U23-S07ZBR - see PMB 10044		USB Cable: Power Plus Connector, 7ft. Straight		
CBA-U15-S15ZAR	CBA-U35-S15ZBR (has heavier gauge wire vs. CBA-U35-S15ZAR, can support 5V and 12V power, scanner dependent)  CBA-U35-S15ZAR ► Discontinued 2/2019, now use CBA-U35-S15ZBR - see PMB 10044		USB Cable: Power Plus Connector, 15ft. Straight		
CBA-U14-C09ZAR ► Discontinued 10/31/2012, PMB 2152	CBA-U34-C09ZAR		USB Cable: Power Plus Connector, 9ft. Coiled		
CBA-U08-C15ZAR  ► Discontinued 12/2023 see PMB 11157	CBA-U28-C15ZBR (has heavier gauge wire vs. CBA-U28-C15ZAR, can support 5V and 12V power, scanner dependent)  CBA-U28-C15ZAR ► Discontinued 4/2020, now use CBA-U28-C15ZBR - see PMB 10343		USB Cable: Power Plus Connector, 15ft. Coiled		
<b>RS232 Cables</b>					
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>	
CBA-R01-S07PBR		RS232 Cable:STD-DB9 Female, TxD on 2, 7ft. Straight	► Includes improved TTL current limit protection circuitry vs. CBA-R01-S07PAR	Requires external power supply	
CBA-R02-C09PAR		RS232 Cable:STD-DB9 Female, TxD on 2, 9ft. Coiled		Requires external power supply	
CBA-R03-C12PAR		RS232 Cable:STD-DB9 Female, TxD on 2, 12ft. Coiled		Requires external power supply	
CBA-R06-C20PBR		RS232 Cable:STD-DB9 Female, TxD on 2, 20ft. Coiled	► Includes improved TTL current limit protection circuitry vs. CBA-R06-C20PAR	Requires external power supply	

CBA-R49-C09ZAR		RS232 Cable: True Cvtr, STD DB9 Female, PWR Pin 9, 9ft coiled - Freezer Rated	<ul style="list-style-type: none"> <li>▶ This cable is recommended for use with the VC70.</li> <li>▶ Cable provides <math>\pm 5V</math> signaling (RS232C) needed by some older PLC's which may not support TTL signalling</li> <li>▶ Cable and strain relief are rated for freezer environment use (-30°C) and is recommended for use with all VC70 installations, regardless of temperature in the environment.</li> <li>▶ NOTE: DS22xx not designed to be used in freezer environments.</li> </ul>	
CBA-R46-C09ZBR		RS232 Cable: True Cvtr, DB9 Female, Pwr Pin 9, TxD on 2, 9ft. Coiled	<ul style="list-style-type: none"> <li>▶ Cable provides <math>\pm 5V</math> signaling (RS232C) needed by some older PLC's which may not support TTL signalling</li> </ul>	
CBA-R37-C09ZBR		RS232 Cable: STD-DB9 Female, PWR Pin 9, 9ft coiled	<ul style="list-style-type: none"> <li>▶ This cable is recommended for use with the VH10, VC80, 8585/8595, and 8515.</li> <li>▶ CBA-R49-C09ZAR is recommended to be used with VC70.</li> <li>▶ Includes improved TTL current limit protection vs. CBA-R37-C09ZAR.</li> </ul>	
CBA-R73-C09ZAR		RS232 Cable: True Cvtr, DB9 Male, Pwr Pin 9, TxD on 2, 9ft. Coiled	<ul style="list-style-type: none"> <li>▶ Cable provides <math>\pm 5V</math> signaling (RS232C) needed by some older PLC's which may not support TTL signalling</li> </ul>	
CBA-R32-S07PAR		RS232 Cable: True Cvtr, DB9 Female, TxD on 2, 7ft. Straight	<ul style="list-style-type: none"> <li>▶ Cable provides <math>\pm 5V</math> signaling (RS232C) needed by some older PLC's which may not support TTL signalling</li> </ul>	Requires external power supply





**Siemens Nixdorf Beetle POS Terminal RS232 Cables**

Part Number	Picture	Description	Notes	Required Items
CBA-R08-S07ZBR		RS232 Cable: Nixdorf Beetle-5V Direct Power Cable 7ft. Straight	<ul style="list-style-type: none"> <li>▶ Includes improved TTL current limit protection circuitry vs. CBA-R08-S07ZAR</li> </ul>	
CBA-R09-C09ZAR		RS232 Cable: Nixdorf Beetle-5V Direct Power Cable 9ft. Coiled		
CBA-R10-S07ZBR		RS232 Cable: Nixdorf Beetle-12V Direct Power, 7ft. Straight	<ul style="list-style-type: none"> <li>▶ Includes improved TTL current limit protection circuitry vs. CBA-R10-S07ZAR</li> </ul>	


**Other POS Terminal RS232 Cables**

Part Number	Picture	Description	Notes	Required Items
CBA-R24-C20ZAR		RS232 Cable: Fujitsu Team POS 500 ICL, 20ft Coiled		
CBA-R31-C09ZAR		CBL:RS232 (NCR7448) 9FT,CLD		




CBA-R47-C09ZAR		CBL:RS232 (NCR AUX PORT) 9FT, CLD		
25-32465-26		RS232 Cable: Datalogic Magellan scanner Auxiliary Port, 6ft Coiled	► RJ50 cable connects to Datalogic Magellan Slot Scanner Auxiliary Port	
CBA-R28-C09ZAR		RS232 Cable: Verifone Ruby, 9ft, Coiled		
<b>IBM 468x/469x POS Cables</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
CBA-M61-S07ZAR		IBM 468x/9x, Port 9B Cable, 7ft. Straight	► Port 9B connection provides 5V power. ► Supports host auto-detect so configuration barcode is not needed to put device into IBM Host mode.	
<b>Scanner Emulation Cables - Not supported on DS22xx</b>				
<b>Synapse Adapter Cables - Not supported on DS22xx</b>				
<b>Terminal Specific Cables</b>				
CBA-A51-S16ZAR		Auxiliary Scanner Cable to MP6000/MP7000, RS232 Serial	► Allows handheld scanners to be used with MP6000/MP7000 for scanning heavy/awkward items. ► 5 meter length ► RS232 serial connection to scanner ► Connects to AUX2 port on MP6000/MP7000. ► Provides power to corded scanners. ► NOTE: MP6000/MP7000 supports maximum of 2 auxiliary scanners.	
<b>Misc</b>				
<b>Part Number</b>	<b>Picture</b>	<b>Description</b>	<b>Notes</b>	<b>Required Items</b>
STND-GS00UNC-04		Universal Gooseneck Intellistand (Black color)	► Stand is compatible with LS2208, LI2208, LS4208, DS4208, DS4308, DS2208, DS8108 ► Stand has scanner trigger magnets in both nose and base. ► Not compatible with DS2278	

20-71043-04R		Gooseneck Intellistand (Black color)	<ul style="list-style-type: none"> <li>▶ Stand is compatible with DS4308, DS2208, and DS8108</li> <li>▶ Not compatible with DS2278</li> </ul>	
20-71043-0BR		Gooseneck Intellistand (White color)	<ul style="list-style-type: none"> <li>▶ Typically used with Heathcare (HC) versions of scanner.</li> <li>▶ Stand is compatible with DS4308, DS4608, DS2208, and DS8108.</li> </ul>	
22-71043-0BR		Weighted Gooseneck Intellistand (White color)	<ul style="list-style-type: none"> <li>▶ Stand features a weighted base.</li> <li>▶ Typically used with Heathcare (HC) versions of scanner.</li> <li>▶ Stand is compatible with DS4308, DS4608, DS2208, and DS8108.</li> </ul>	
22-71043-07R		Weighted Gooseneck Intellistand (Black color)	<ul style="list-style-type: none"> <li>▶ Stand features a weighted base.</li> <li>▶ Stand is compatible with DS4308, DS4608, DS2208, and DS8108</li> </ul>	


**Power Supplies/Power Cords**

Part Number	Picture	Description	Notes	Required Items
25-MCXUSB-01R		Micro USB Cable	<ul style="list-style-type: none"> <li>▶ Used to charge DS2278 without the need for a cradle.</li> <li>▶ Cable plugs into micro-USB port on the bottom of the scanner.</li> <li>▶ Cable will charge battery to 14 hours of scanner usage in 1 hour when charging via PC USB port or in 1/2 hour when using USB Power Supply (PWR-WUA5V6W0WW)</li> <li>▶ NOTE: Other micro USB cables (i.e. 25-124330-01R) may not fit on the USB port on the DS2278.</li> <li>▶ Cable length is 60"</li> </ul>	If scanner will not be charged via USB port on PC, use USB Power Supply (PWR-WUA5V6W0WW) and country specific AC Clip (if needed)

PWR-WUA5V6W0WW		USB Power Supply	<ul style="list-style-type: none"> <li>▶ Can be used to charge DS2278 directly from its micro-USB port or can be used to power Presentation Cradle to create a "charge-only" cradle solution for customers wanting to pair DS2278 directly to host.</li> <li>▶ Includes four international plugs for use in US, UK, EU, and AU. Additional plugs can be purchased separately for other countries.</li> <li>▶ 5.2V, 1.2A, 6W output</li> <li>▶ Provides US DOE Level VI compliance for power efficiency</li> </ul>	<p><u>To charge DS2278 directly from micro-USB port:</u> Micro USB Cable (25-MCXUSB-01R)</p> <p><u>To power Presentation Cradle:</u> Presentation Cradle (CR2278-PC10004WW) AND USB Cable (CBA-U21-S07ZBR)</p>
PWR-WUA5V6W0WHT		USB Power Supply, White color	<ul style="list-style-type: none"> <li>▶ Can be used to charge DS2278 directly from its micro-USB port or can be used to power Presentation Cradle to create a "charge-only" cradle solution for customers wanting to pair DS2278 directly to host.</li> <li>▶ Includes four international plugs for use in US, UK, EU, and AU. Additional plugs can be purchased separately for other countries.</li> <li>▶ 5.2V, 1.2A, 6W output</li> <li>▶ Provides US DOE Level VI compliance for power efficiency</li> <li>▶ NOTE: SKU is restricted sale. May require Zebra Product Management approval to order.</li> </ul>	<p><u>To charge DS2278 directly from micro-USB port:</u> Micro USB Cable (25-MCXUSB-01R)</p> <p><u>To power Presentation Cradle:</u> Presentation Cradle (CR2278-PC10004WW) AND USB Cable (CBA-U21-S07ZBR)</p>
CN-000803-01		<u>Spare/Replacement</u> USB Power Supply AC Clip for Australia (AUS)	<ul style="list-style-type: none"> <li>▶ This AC Clip is normally included with PWR-WUA5V6W0WW</li> <li>▶ 2 pin Australia plug</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-02		USB Power Supply AC Clip for Argentina (ARG)		USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-03		USB Power Supply AC Clip for Korea (KOR)		USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-04		<u>Spare/Replacement</u> USB Power Supply AC Clip for US (US)	<ul style="list-style-type: none"> <li>▶ This AC Clip is normally included with PWR-WUA5V6W0WW</li> <li>▶ 2 pin US plug</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-05		<u>Spare/Replacement</u> USB Power Supply AC Clip for Europe (EU)	<ul style="list-style-type: none"> <li>▶ This AC Clip is normally included with PWR-WUA5V6W0WW</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-06		<u>Spare/Replacement</u> USB Power Supply AC Clip for UK (UK)	<ul style="list-style-type: none"> <li>▶ This AC Clip is normally included with PWR-WUA5V6W0WW</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-07		USB Power Supply AC Clip for China (CHN)	<ul style="list-style-type: none"> <li>▶ straight pins China plug</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-08		USB Power Supply AC Clip for Brazil (BRA)	<ul style="list-style-type: none"> <li>▶ 2 pin Brazil plug</li> </ul>	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-09		USB Power Supply AC Clip for India (IND)		USB Power Supply (PWR-WUA5V6W0WW)
PWR-WUA5V4W0US		Power Supply (US)	<ul style="list-style-type: none"> <li>▶ Used when connecting communication cables labeled above as "Requires external power supply".</li> <li>▶ For use in US, CA, MX, JP, TW.</li> <li>▶ 5.2V, 1.1A, 5.7W</li> <li>▶ Provides US DOE Level VI compliance for power efficiency.</li> <li>▶ Replaces PWRS-14000-253R</li> </ul>	

PWR-WUA5V4W0IN		Power Supply (India)	<ul style="list-style-type: none"> <li>▶ Used when connecting communication cables labeled above as "Requires external power supply".</li> <li>▶ For use in India.</li> <li>▶ 5.2V, 1.1A, 5.7W</li> <li>▶ Provides US DOE Level VI compliance for power efficiency.</li> <li>▶ Replaces PWRS-14000-254R</li> </ul>	
PWR-WUA5V4W04C		Power Supply (EU, UK, Brazil, Australia, China)	<ul style="list-style-type: none"> <li>▶ Used when connecting communication cables labeled above as "Requires external power supply".</li> <li>▶ Includes AC adapter clips for use in EU, UK, Brazil, Australia and China.</li> <li>▶ 5.2V, 1.1A, 5.7W</li> <li>▶ Provides US DOE Level VI compliance for power efficiency.</li> </ul>	
23844-00-00R		AC Line Cord	▶ This AC Line Cord is for use in North America. See the <b>AC Line Cords by Country</b> TAG for comparable line cords to use in other countries.	

**Batteries**

Part Number	Picture	Description	Notes	Required Items
BTRY-DS22EAB0E-00		DS2278 Spare Battery (2400 mAh)	<ul style="list-style-type: none"> <li>▶ Li-Ion Battery</li> <li>▶ Battery capable of providing 110,000 scans at 60 Scans per Minute or 50,000 scans at 10 Scans per Minute (84 hours of use)</li> </ul>	
BTRY-DS22EAB0E-00Y (India only) ▶ Discontinued 1/2020 - see PMB 10261				